

Hints & Tips

Every letter published receives an extra issue of the Journal added to your subscription!

hints@psioncomputer.com



The following Hints & Tips have been shamelessly stolen from Martin Guthrie's excellent web site www.pscience5.net!

EPOC.

Press Ctrl+Tab from the system screen to bring up your Psion explorer which will allow you to view your Z drive when selecting which drive to view.

- o Turning off "Show System Folder" in preferences from the system screen dramatically increases the file browsing speed of your Psion.
- o In the owner dialog press Shift+Control+F to bring up a font dialog which enables you to change font style and the font face.
- o Press Fn+System to cycle through running applications.
- o In Calc pressing Shift+Ctrl+I brings up a list of keyboard shortcuts.
- o You can increment and decrement the snooze period for alarms to one minute intervals using ? and M or 5 minute intervals using Space.
- o In most text entry situations (eg. in Word, Agenda, Email, etc.), pressing Ctrl+Shift+Fn+C brings up an 'Insert special character' box - all the standard symbol characters in ASCII.

- o In any program, pressing Ctrl+Shift+Fn+S takes a screenshot.
- o Ever wanted to do a very soft reset?!? Pressing Ctrl+Shift+Fn+K in the system screen performs a soft reset - but without closing any of your open programs (or losing any of their data).

SIBO.

The following SIBO Hints & Tips have been stolen else where.

How to assign an application button (like Data, Word etc.) to a different application.

Highlight the application to which you wish to assign a button and press Psion + A or choose Assign button from the Apps menu. Set the Modifier line to None if you want the application button on its own to take you to the application, or Control + if you want to use the Control key and the application button. Set the Button line to the button you wish to use and press Enter.

How to show the clock when running application.

In most applications, press Fn + Menu to show or hide the Status window.

How do I use Calc memories in OPL?

You can use the values stored in Calc memories from OPL without declaring them by simply referring to them by their original names: M0 to M9.

How do I show more than one To-do list at a time?

Press Psion + Q or select Set preferences from the Special menu then press Psion + T or select To-do view from the View preferences menu. Enter the number of lists you would like to be able to see at once in the To-do view and press Enter.